

0.56 inch (14.20mm), White Triple Digit 7-segment SMD LED Display

Technical Data Sheet

Features

- 0.56 inch (14.20mm) digit height.
- The thickness is thinness than tradition display.
- Packaged in tape and reel for SMT manufacturing.
- Low current operation.
- Excellent characters appearance.
- Categorized for luminous intensity.
- Available in CA and CC.
- The product itself will remain within RoHS compliant Version.



Descriptions

- The KW3-S561AWB / KW3-S561CWB is a 0.56 inch (14.20mm) height triple digit display.
- The display provides excellent reliability in bright ambient light.
- The device is made with white segments and black surface.

Applications

- Home appliances
- Game machine
- Instrument panels
- Digital readout displays

Device Selection Guide

Part No.	Emitting Color	Polarity
KW3-S561AWB	White	Common Anode
KW3-S561CWB	White	Common Cathode

Spec No.:S561-Y024Date:16-Mar-2018Issue No.:G-001-Rev-3E-mail:sales@luckylight.cnLuckylight Electronics Co., Ltdhttp://www.luckylight.cn


Copyright © 2017 Luckylight All Rights Reserved Page: 1/9





0.56 inch (14.20mm), White Triple Digit 7-segment SMD LED Display


Technical Data Sheet


Package Dimension











Notes:

- 1. All dimensions are in millimeters (inches).
- 2. Tolerance is ± 0.25 mm (.010") unless otherwise noted.
- 3. The gap between the reflector and PCB shall not exceed 0.25mm.

Spec No.:S561-Y024Date:16-Mar-2018Issue No.:G-001-Rev-3E-mail:sales@luckylight.cnLuckylight Electronics Co., Ltdhttp://www.luckylight.cn

Copyright © 2017 Luckylight All Rights Reserved Page: 2 / 9




0.56 inch (14.20mm), White Triple Digit 7-segment SMD LED Display

Technical Data Sheet

Internal Circuit Diagram:


Internal Circuit Diagram (Common Anode)

KW3-S561AWB



Internal Circuit Diagram (Common Cathode)

KW3-S561CWB



Spec No.: S561-Y024
Issue No.: G-001-Rev-3
Luckylight Electronics Co., Ltd
Copyright © 2017 Luckylight All Rights Reserved

Date: 16-Mar-2018
E-mail: sales@luckylight.cn
http:// www.luckylight.cn

Page: 3/9



0.56 inch (14.20mm), White Triple Digit 7-segment SMD LED Display

Technical Data Sheet

Absolute Maximum Ratings at Ta=25℃

Parameters	Symbol	Max	Unit
Power Dissipation Per Segment	P_d	35	mW
Peak Forward Current Per Segment (1/10 Duty Cycle, 0.1ms Pulse Width)	I _{FP}	50	mA
Forward Current Per Segment	l _F	10	mA
Reverse Voltage Per Segment	V _R	5	V
Operating Temperature Range	T_{opr}	-40°C to +100°C	
Storage Temperature Range	T_{stg}	-40℃ to +105℃	
Soldering Temperature	T _{sld}	260℃ for 5 Seconds	

Electrical Optical Characteristics at Ta=25℃

Parameters	Symbol	Min.	Тур.	Max.	Unit	Test Condition	
Average Luminous Intensity	lv	50	100		mcd	IF=10mA (Note 1, 2)	
Luminous Intensity Matching Ratio	I _{v-m}			2:1		IF=10mA	
Chromoticity Coordinates	x		0.30			- IF=10mA (Note 3)	
Chromaticity Coordinates	у		0.31				
Forward Voltage Per Segment	VF		2.90	3.10	V	IF=10mA	
Reverse Current Per Segment	I _R			50	μA	VR=5V	

Notes:

- 1. Luminous Intensity is a average value which is measured one 7-segment. Tolerance of Luminous Intensity: ±10%.
- 2. Excess driving current and / or operating temperature higher than recommended conditions may result in severe light degradation or premature failure.
- 3. The chromaticity coordinates (x, y) is derived from the 1931 CIE chromaticity diagram.

Spec No.: S561-Y024

Issue No.: G-001-Rev-3

Luckylight Electronics Co., Ltd

Copyright © 2017 Luckylight All Rights Reserved

Date: 16-Mar-2018

E-mail: sales@luckylight.cn http:// www.luckylight.cn

D 4/0


Page: 4/9





0.56 inch (14.20mm), White Triple Digit 7-segment SMD LED Display


Technical Data Sheet

Typical Electrical / Optical Characteristics Curves (25°C Ambient Temperature Unless Otherwise Noted)











Luminous Intensity & Forward Current



Forward Current Derating Curve



Spec No.: S561-Y024 Issue No.: G-001-Rev-3 Luckylight Electronics Co., Ltd Copyright © 2017 Luckylight All Rights Reserved

http:// Page: 5/9

Date: 16-Mar-2018 E-mail: sales@luckylight.cn

www.luckylight.cn



0.56 inch (14.20mm), White Triple Digit 7-segment SMD LED Display

Technical Data Sheet


Chromaticity Coordinates Specifications for Bin Rank

Color Bin at IF = 10mA

Bin Code	CIE 1931 Chromaticity Coordinates				
W1	Х	0.284	0.284	0.304	0.304
	у	0.278	0.311	0.332	0.298
W2	Х	0.304	0.304	0.324	0.324
	у	0.268	0.298	0.322	0.292
W3	Х	0.304	0.304	0.324	0.324
	у	0.298	0.332	0.352	0.322

Tolerance on each Hue (x, y) bin is \pm -0.01.

CIE 1931Chromaticity Coordinates



Spec No.: S561-Y024
Issue No.: G-001-Rev-3
Luckylight Electronics Co., Ltd

Copyright © 2017 Luckylight All Rights Reserved Page:

Date: 16-Mar-2018

E-mail: sales@luckylight.cn

http:// www.luckylight.cn


Page: 6/9




0.56 inch (14.20mm), White Triple Digit 7-segment SMD LED Display

Technical Data Sheet


The Products In The Reel Of Direction



Label Direction & Content In The Roll



User Feed Direction



Package Criteria

- 1. Total unit per reel is 500PCS.
- 2. Max 5 reels/2500PCS are packaged in each carton.

Spec No.:S561-Y024Date:16-Mar-2018Issue No.:G-001-Rev-3E-mail:sales@luckylight.cnLuckylight Electronics Co., Ltdhttp://www.luckylight.cn

Copyright © 2017 Luckylight All Rights Reserved Page: 7/9



0.56 inch (14.20mm), White Triple Digit 7-segment SMD LED Display

Technical Data Sheet

Terms and conditions for the usage of this document

- 1. The information included in this document reflects representative usage scenarios and is intended for technical reference only.
- 2. The part number, type, and specifications mentioned in this document are subject to future change and improvement without notice. Before production usage customer should refer to the latest datasheet for the updated specifications.
- 3. When using the products referenced in this document, please make sure the product is being operated within the environmental and electrical limits specified in the datasheet. If customer usage exceeds the specified limits, Luckylight will not be responsible for any subsequent issues.
- 4. The information in this document applies to typical usage in consumer electronics applications. If customer's application has special reliability requirements or have life-threatening liabilities, such as automotive or medical usage, please consult with Luckylight representative for further assistance.
- 5. The contents and information of this document may not be reproduced or re-transmitted without permission by Luckylight.
- 6. The LEDs should be operated with forward bias. The driving circuit must be designed so that the LEDs are not subjected to forward or reverse voltage while it is off. If reverse voltage is continuously applied to the LEDs, it may cause migration resulting in LED damage.

Spec No.: S561-Y024
Issue No.: G-001-Rev-3
Luckylight Electronics Co., Ltd

Copyright © 2017 Luckylight All Rights Reserved

Date: 16-Mar-2018
E-mail: sales@luckylight.cn

http:// www.luckylight.cn

Page: 8/9



0.56 inch (14.20mm), White Triple Digit 7-segment SMD LED Display


Technical Data Sheet

Precautions for Use

1. Caution in ESD

Static electricity and surge damages the LED. It is recommended to use a wrist band or anti-electrostatic glove when handling the LED. All devices equipment and machinery must be properly grounded.


2. SMT Soldering Condition



Reflow Soldering (Two times only)		Soldering	Soldering Iron (One time only)		
Pre-heat	120~150℃	Temperature	300℃ Max.		
Pre-heat time	120 sec. Max.	Soldering time	3 sec. Max.		
Peak temperature	260°C Max.				
Soldering time	5 sec. Max.				

3. Circuit Design Notes:

- 1. Protective current-limiting resistors may be necessary to operate the LEDs within the specified range.
- 2. LEDs mounted in parallel should each be placed in series with its own current-limiting resistor.



Spec No.: S561-Y024
Issue No.: G-001-Rev-3
Luckylight Electronics Co., Ltd
Copyright © 2017 Luckylight All Rights Reserved

Page: 9/9

16-Mar-2018

sales@luckylight.cn

www.luckylight.cn

Date:

E-mail:

http://